

VIBRATION RANGE

# AFE SUITCASE

## Suitcase-type electrical converters

The AFE suitcase-type electrical converters stand out for their reliability and versatility, allowing for the connection of multiple high-frequency needles to the same equipment.



**+ Safety**

The low 42V safety voltage eliminates the possibility of electric shock.




**+ Reliability**

Superior quality switch that disconnects the equipment when an overcurrent is detected.



**+ Protective housing**

Offers a double function: Shields the converter from external impacts and is simple to clean against concrete splashes.



**+ Mobility**

Its suitcase-style shell allows for easier transport.

- 5 meters of cable
- Voltage/frequency inputs available upon request :
  - Tri-phase: 230V 3~50Hz and 230V 3~60Hz
  - Single-phasé: 230V 3~50Hz, 230V 3~60Hz and 110V 1~60Hz

### Connection possibilities

| MODEL       | M38 | M5 | M6 | M7 | M8 |
|-------------|-----|----|----|----|----|
| AFE 1000M P | x1  | x1 | -  | -  | -  |
| AFE 2000M P | x2  | x2 | x1 | x1 | x1 |
| AFE 2000 P  | x2  | x2 | x1 | x1 | x1 |

\* Number of M-AFP ENAR pokers that can be connected at the same time to each AFE model.



### Technical Data

| MODEL       | Weight (kg) | N° plugs | Input     |                   | Output      |                   |
|-------------|-------------|----------|-----------|-------------------|-------------|-------------------|
|             |             |          | Power     | Tension/Frequency | Power       | Tension/Frequency |
| AFE 1000M P | 20          | 1        | 1.3 KW 6A | 230V 1 ~ 50Hz     | 1.0 KVA 13A | 42V 3 ~ 200Hz     |
| AFE 2000M P | 29          | 2        | 2.0 KW 9A | 230V 1 ~ 50Hz     | 1.6 KVA 23A | 42V 3 ~ 200Hz     |
| AFE 2000 P  | 29          | 2        | 2.8 KW 4A | 400V 3 ~ 50Hz     | 1.6 KVA 23A | 42V 3 ~ 200Hz     |